


sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1




Apply 111 into 1 and feed as shown and secure using 258.

Tool List	PHILLIPS NO2		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***3	FD-3020UK	ASSY BASE BOX	1				
***111	253-5460-01	AIR VENT BLACK	1				
***258	000-T00420-0B	M4X20 MSCR TH BLK	4				

Top level No	0	Level	2
Part number	0		
Description	0		
Page	(1 / 4)		

Name	Richard Ford
Date	08/05/2006
Rev.	1




Tool List	10MM SOCKET	ADJ SPANNER	

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
****1	ORP-3001UK	FRAME BASE	1				
****101	601-5699UK13-01	LEG ADJ M16X130 1L/NUT	6				
****102	MA1019	CASTER 75	6				
****202	030-000620-S	M6X20 BLT W/S PAS	16				
****203	060-F00600	M6 WSHR FORM A FLT PAS	16				



Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page	(1 / 1)		

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1




Apply 1 to 3 in position shown and secure using 219&260.



CAUTION
Two person handling required

Apply 42 to 1 in position shown and secure using 247&248.




Tool List	13MM SOCKET	RACHET EXT B

Top level No	0	Level	2
Part number	0		
Description	0		


Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***1	ORP-2051UK	COCKPIT CABI	1				
***42	ORP-2055UK	JOINT PLATE REAR	1				
***219	060-F00800	M8 WSHR FORM A FLT	6				
***247	030-000820-SB	M8X20 BLT W/S BLK	4				
***248	030-000830-SB	M8X30 BLT W/S BLK	4				
***260	030-000830-S	M8 BLT SPR PAS	6				

sega work instructions


Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 55 to 1 in position shown and secure using 212,244&254.




Apply 29 to 1 in position shown and secure using 210&212.



Apply 54 to 1 in position shown and secure using 226.

Apply 53 to 1 in position shown and secure using 226.

TOP VIEW




Tool List	PHILLIPS NO2	10MM SOCKET

Top level No	0	Level	2
Part number	0		
Description	0		
Page		(3 / 10)	

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***29	ORP-2019UK	COVER KNEE	1				
***53	ORP-2060UK	BONNET BRKT L	1				
***54	ORP-2061UK	BONNET BRKT R	1				
***55	ORP-2062UK	FOOTWELL BRACKET R	1				
***210	030-000620-S	M6X20 BLT SPR PAS	3				
***212	060-F00600	M6 WSHR FORM A FLT	7				
***226	000-P00512-W	M5X12 MSCR PAN W/FS PAS	4				
***244	030-000630-S	M6X30 BLT SPR PAS	3				
***254	030-000650	M6X50 BLT PAS	1				

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 36 to 1 in position shown and secure using 210,212&239.


Tool List	10MM SOCKET		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***36	ORP-2026UK	BULK BOARD HOLDER	1				
***210	030-000620-S	M6X20 BLT W/S PAS	3				
***212	060-F00600	M6 WSHR FORM A FLT PAS	3				
***239	000-T00408-0B	M4X8 MSCR TH BLK	4				

Top level No	0	Level	2
Part number	0		
Description	0		
	Page	(6 / 10)	

Name	Richard Ford
Date	08/05/2006
Rev.	1

Apply 5 to 1 in position shown and secure using 210&244.




Tool List	10MM SOCKET		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***5	FD-2054UK	CONTROL PANEL BRKT	1				
***244	030-000630-S	M6X30 BLT W/S PAS	2				
***248	030-000830-SB	M8X30 BLT W/S BLK	2				

Top level No	0	Level	2
Part number	0		
Description	0		
	Page	(7 / 10)	

Name	Richard Ford
Date	08/05/2006
Rev.	1

Apply 58 to 106 in positions shown and secure using 201.





Apply 58 to 1 in position shown and securs using 253.

Tool List	PHILLIPS NO2		


Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***58	FD-2065UK	SPEAKER MTG BRKT	2				
***106	130-365-568UK	SPEAKER-EPILITICAL-8 OHMS 15W	2				
***201	000-P00412-W	M4X12 MSCR PAN W/FS PAS	8				
***253	000-P00420-W	M4X20 MSCR PAN W/FS PAS	4				

Top level No	0	Level	2
Part number	0		
Description	0		
Page		(8 / 10)	

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 38 to 1 in position shown and secure from the bottom using 207 .



Tool List	PHILLIPS NO2		



Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***38	ORP-2028UK	ASSY BULK BOARD COVER	1				
***239	000-T00412-0B	M4X8 MSCR TH BLK	4				

Top level No	0	Level	2
Part number	0		
Description	0		
Page		(9 / 10)	


Title: WCCF 2P

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 46 to 45 in positions shown securing from below using 252 as shown.



Apply 45 to 38 in position shown and secure using 250 from above and 238&251 from below.

Tool List	7MM SOCKET	PHILLIPS NO2


Top level No	0	Level	2
Part number	0		
Description	0		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***45	ORP-2035UK	LENS FLASH	1				
***46	ORP-2036UK	HOLDER PIN	2				
***238	050-F00400	M4 FLG NUT SER PAS	2				
***250	000-F00416	M4X16 MSCR CSK	2				
***251	068-441616	M4 WSHR 16OD FLT PAS	2				
***252	000-F00420	M4X20 MSCR CSK	2				

sega work instructions


Name	Richard Ford
Date	08/05/2006
Rev.	1

Apply 301 to 101,102&103 in positions shown.



Apply 204 to 1 over 301 in position shown.

Apply 105 to 1 over 103 as shown and shrink.



Tool List	HEAT GUN	7MM SOCKET	


Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
****105	310-5029-D508	HEAT SHRINK SLEEVING 50.8DIA	1				
****204	050-F00400	M4 NUT FLG SER PAS	1				
****301	ORP-60033UK	WH AC OUT PRIMARY	1				

Top level No	4FD-0000UK	Level	2
Part number	FD-2070UK		
Description	ASSY AC UNIT		
Page		(2 / 3)	

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1


Please note that this diagram will be used when the moulding has been applied to the cntrl pnl.



Apply 16 into 9 in positions shown.




16



234

Apply to 15 covering 16 as shown and secure using fixings supplied with 9.




8

Apply 8 over 16 onto 9 as shown.

15

Apply 12 to 11 securing with 234 as shown.



11

Apply 11 to 15 securing with fixings supplied with 9 also.

12

Tool List	HEX KEY SET	19MM SOCKET	


Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***8	FR-2003UK	HANDLE COLLAR	1				
***11	SPG-2001	STEERING WHEEL	1				
***12	FRI-2002	EMBLEM	1				
***15	FRI-2055	BOSS COVER	1				
***16	DYN-1270	STOPPER KEY	1				
***234	FAS-20013	M4X16 SKT CAP CRM	4				

Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page		(2 / 2)	

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1

Apply 103&104 to 101&102 as shown below.




Apply 301 to 101&102 as shown.

Tool List			
-----------	--	--	--


Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
****1	FD-2021UK	SW PLATE	1				
****101	509-6001-B	BTN RND 12V BLUE 22-0665-6	1				
****102	509-6001-Y	BTN RND 12V YELLOW 22-2060-4LP	1				
****103	LT1051	LED CLUSTER YEL 161-12103-4	1				
****104	LT-1053	LED CLUSTER BLU 161-12103-6	1				

Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page	(1 / 1)		

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 6 to 1 in position shown and secure using 202,210&212.




Tool List	13MM SOCKET		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
**6	FD-0300UK	COIN TOWER ASSY	1				
**202	068-852216-0B	M8 WSHR 22OD FLT BLK	4				
**210	050-U00800	M8 NUT NYLOK PAS	2				
**212	030-000820-S	M8X20 BLT W/S PAS	2				

Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page	(4 / 6)		

Name	Richard Ford
Date	08/05/2006
Rev.	1




Apply 301 to 102 as shown.

Tool List	TERMINAL		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***102	390-0240-40UK	FL UNIT 240V 40W	1				
***301	FD-66036UK	WH FL UNIT	1				



Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page	(1 / 6)		

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 302 to 101 in positions shown.

Apply 106&107 to 3 in positions shown.




Tool List			

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***106	LB1102	STICKER DANGEROUS VOLTAGE	1				
***107	LB1104	STICKER CAUTION, HOT SURFACE	1				
***302	FD-66037UK	WH LED BILLBOARD	1				


Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page	(4 / 6)		

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 1&2 to 3 in positions shown and secure using 205.




Tool List	PHILLIPS NO2		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***1	FD-0501UK	PLATE L	1				
***2	FD-0502UK	PLATE R	2				
***205	000-T00416-0B	M4X16 MSCR TH BLK	10				

Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page	(5 / 6)		

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 105 to 12 in position shown and secure.

Hook 8 into place over 12 as shown.


Apply 12 to 1 in position shown and lock.

Tool List	BOX SPANNER	11MM SOCKET

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***8	PTR-0006-01UK	SECURITY BAR	1				
***12	220-5725-05B	DOOR SINGLE MINI H SECURITY BLK	1				
***105	220-5574-110UK	LOCK-KEY DIFFERS 11M W/O CAM	1				

Top level No	4FD-0000UK	Level	2
Part number	FD-0300UK		
Description	ASSY CCT		
Page		(5 / 5)	

Name	Richard Ford
Date	08/08/2006
Rev.	1



Apply 103 to102 in location shown and shrink.

Apply 302 in locations shown and secure using 204.

Apply 301 in locations shown and secure to 1 using 203.

Please note that the harness shown will be shielded and are not shown for illustration purposes.


Tool List	7MM SOCKET	10MM SOCKET	
	HEAT GUN		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***103	310-5029-D508	HEAT SHRINK SLEEVING 50.8D	5CM				
***203	050-F00400	M4 NUT FLG SER PAS	1				
***204	050-F00600	M6 NUT FLG SER PAS	1				
***301	FD-66032UK	WH AC BRKT FD	1				
***302	FD-66042UK	WH EARTH BRAID STRAP	1				

Top level No	4FD-0000UK	Level	2
Part number	FD-0660UK		
Description	ASSY AC UNIT		
Page (2 / 2)			

Name	Richard Ford
Date	08/05/2006
Rev.	1

Apply 16 to 104 as shown and secure using 210.



Fit 21 to the rear of 104 as shown.

Apply 16 to 2 in positions shown securing with 207 as shown.

Tool List	PHILLIPS NO2		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***16	STC-1607	SP MOUNT BRKT	2				
***21	SRT-2409	SHOULDER PAD	2				
***104	130-5162-01	GULL BOX SPEAKER	2				
***207	000-P00410-W	M4X10 MSCR PAN W/FS PAS	8				
***210	012-P03512-F	N6X1/2" S/TAP FLG PAS	8				


Top level No	4FD-0000UK	Level	2
Part number	FD-2400UK		
Description	ASSY SEAT		
Page	(3 / 10)		

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1

Apply 6 to the underneath of 3 in position shown and secure using 201&205 as shown.

Fit 9 to 6 using 207 then apply 108 to 9 securing with 209.



Tool List	13MM SOCKET		
	PHILLIPS NO2		


Top level No	4FD-0000UK	Level	2
Part number	FD-2400UK		
Description	ASSY SEAT		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***4	ORP-2404UK	SEAT BASE	1				
***9	FRI-3309	CABLE BEAR BRKT	1				
***109	280-A00900-A	ROUTER TWIST D9 ADH	4				
***202	030-000850-SB	M8X50 BLT W/S BLK	8				
***206	000-T00408-0B	M4X8 MSCR TH BLK	4				
***209	000-T00616-0B	M6X16 MSCR TH BLK	2				

Title: FORD DX

sega work instructions

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 301&302 to 104 in locations shown.

Apply 107 to 105 then secure 105 to 1 in position shown and secure using 201.

Apply 104 to 1 in position shown and secure using 202 from the underneath of the board.


Tool List	PHILIPS NO1		

Top level No	4FD-0000UK	Level	2
Part number	FD-4200UK		
Description	ASSY ELEC BOARD		
Page	(1 / 2)		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***1	FD-4201UK	WOODEN BASE ELEC	1				
***104	400-0024-0100UK	POWER SUPPLY 24V 100 W	1				
***105	FR-838-001UK	MOTOR CONT ISO HAPP 50-2000-03	1				
***107	OS1011	PCB FEET	4				
***201	012-P03512-F	N6X1/2" S/TAP FLG PAS	4				
***202	000-F00320	M3X20 MSCR CSK PAS	2				
***301	FD-66016UK	WH AC POWER D	1				
***302	FD-66017UK	WH MOTOR IN	1				

Name	Richard Ford
Date	08/05/2006
Rev.	1

Apply 303&304 to locations shown and feed through 108 as shown.





Feed 301&302 through 108&110 also as shown.

Tool List			

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***108	280-A00964-WX	ROUTER TWISTD09 SO.6.4WOOD X BH	1				
***110	280-A02064-WX	ROUTER TWIST BHKL-750-4-01	4				
***303	FD-66018UK	WH MOTOR OUT	1				
***304	FD-66019UK	WH PARALLEL PORT C	1				

Top level No	4FD-0000UK	Level	2
Part number	FD-4200UK		
Description	ASSY ELEC BOARD		
Page		(2 / 2)	

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 302 to locations shown noting the positions above.


Apply 303 to location shown.

Tool List			

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***302	FD-66006UK	WH AUDIO C	1				
***303	FD-66022UK	WH SPRK REAR C	1				

Top level No	4FD-0000UK	Level	2
Part number	FD-4100UK		
Description	ASSY AMP BOARD		
Page	(5 / 5)		

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 308,309,310 &311 to positions shown.


Tool List			

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
*****308	FD-66005UK	WH AUDIO A	1				
*****309	FD-66007UK	WH PARALLEL PORT A	1				
*****310	FD-66010UK	WH PC POWER A	1				
*****311	FD-66011UK	WH BRAKE LIGHT PWR A	1				


Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		
Page	(2 / 2)		

sega work instructions


Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 12&13 to the front of 2 then 106 on the inside to space of 102 when applied the secure from by applying 205 from the outside and 218 from the inside as shown.



PLEASE NOTE THAT I HAVE SHOWN 106 IN DIAGRAM 1 FOR POSITIONING.




Tool List	PHILLIPS NO2		



Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***5	FD-2356UK	BRKT LOWER MOUNT R	1				
***12	FD-2365-AUK	REAR LIGHT TOP	2				
***13	FD-2365-BUK	REAR LIGHT BASE	2				
***102	FD-838-004UK	BRAKE LIGHT LED BRD	1				
***106		SPACER	4				
***205	000-P00445-W	M4X45 MSCR W/S APN PAS	4				
***218	050-U00400	M4 NUT NYLOK PAS	4				
***302	FD-60039UK	WH LED BRAKE LIGHT	1				

Name	Richard Ford
Date	08/05/2006
Rev.	1



Apply 10 to the rear of 2 and 3&9 to the inside as shown and secure using 204 from the rear.



Apply 201,203&204 to the rear of 2 securing it to 1 as shown.

Tool List	T30	PHILLIPS NO2	

Top level No	4FD-0000UK	Level	2
Part number	ORP-3000UK		
Description	ASSY FRAME BASE		

Seq.	Part number.	Description	Qty	Sub Assy	Ord	Tool	S.T
***2	FD-2032UK	REAR FAIRING	1				
***3	FD-2353UK	BRKT SUPT NUM PL	1				
***9	FD-2367UK	SURROUND-NO-PL-FD-1	1				
***10		NUMBER PLATE	1				
***201	000-T00612-0C	M6X12 MSCR TH CRM	4				
***203	000-T00540-0C	M5X40 MSCR TH CRM	2				
***204	008-T00625-0C	M6X25 TMP PRF TH CRM	12				

